



EXPERIENCE THE EXCEPTION

If you relish an emotional listening experience, the M·C·X system is engineered for you. The emphasis is on the realism and musicality, as defined by exceptional fluidity, finesse and control. This is Exposure's highest definition yet of a 21st Century high-end, hi-fidelity system.

<i>Key system features (all components)</i>	<i>Benefits</i>
<ul style="list-style-type: none">• Double-sided printed circuit boards (PCBs)	Good shielding, low impedance signal lines and grounds
<ul style="list-style-type: none">• Mains power transformers with inter-winding shields	Reduction of pick-up from noisy mains supply
<ul style="list-style-type: none">• High-mass aluminium casework	Low levels of induced hum affecting critical circuits, good screening from external fields and low resonance
<ul style="list-style-type: none">• Quality screw terminal smoothing capacitors for main audio power supply	Low impedance supply line over a wide frequency range
<ul style="list-style-type: none">• RJ45-based "exlinks"	Easy control of power up / down and other functions by daisy-chaining units

Prototype images only. Exposure Electronics Ltd reserves the right to re-design / re-engineer the casing/facades of manufactural units.

Exposure Electronics Ltd:
The Works 59 North Street, Portslade, East Sussex BN41 1DH, England.
Tel: +44 1273 423877 Fax: +44 1273 430619



M·C·X
PRE-AMPLIFIER
EXCEPTIONAL FINESSE



*exposure*TM
high fidelity engineering since 1974

**M.G.X. PRE-AMPLIFIER:
EXCEPTIONAL FINESSE**

- Mono printed circuit board (PCB) construction to ensure low cross-talk between channels
- Available with either MM or MC phono cards fitted
- All discrete transistor audio circuits
- Input switching and volume attenuation by high quality reed relays
- X1 gain setting for easy integration into an audio-visual (AV) system when the input is in AV mode
- 12V input and output trigger system allows control of, or from, an AV system



S P E C I F I C A T I O N S

Inputs	Phono MM or MC by plug-in board (XLR or RCA input sockets) 5 x line level inputs, 250mV 1 x CD input, XLR balanced connector
Outputs	2 x XLR, balanced pre-out 1 x RCA, pre-out 1 x RCA, tape output
Communication	External remote control receiver input 12V trigger input 12V trigger output RJ45 input 'exlink' RJ45 output 'exlink'
Power supply input	Internally adjustable for 110V–120V or 220V– 240V, 50 -60Hz
Power consumption	35W with power on, 25W on stand-by
Size (W x D x H)	490 x 414 x 104mm
Weight	20kg