

## Pro-Ject Tuner Box

FM tuner



### Good sound from sound technology

- Metal case shields the electronics from vibrational and electromagnetic interference
- Automatic frequency control (AFC) and adaptive noise cancellation
- Gold plated RCA connection sockets
- Outboard power supply included

### Features

- Small size allows easy placement
- Fine tuning meter, signal strength meter and stereo/mono reception indicator
- The Tuner Box can be switched on & off remotely via a trigger signal
- The remote power-on signal can be relayed to further units

### Technical specifications

Tuning range FM-band:	87,5 - 108,5MHz (50kHz steps)
Programmable presets:	8
Frequency response:	20Hz - 20kHz/±1dB
Noise floor:	-50dB
THD:	0,05% / Δf 75kHz and f mod 1kHz
Stereo separation:	30dB / Δf 75kHz and f mod 1kHz
Sensitivity:	9dB μV mono, 19μV stereo /75 ohms
Antenna input:	1 x co-axial DIN-socket (75 ohms) / US-model F-socket
Line-level output:	1 pair RCA/Phono sockets
Trigger:	12V DC switching voltage
Trigger in and out:	2-pole co-axial Ø 2,5mm jack
Output voltage:	0,775V <sub>eff</sub>
Outboard power supply:	16V/200mA AC, suitable for your country's mains supply
Power consumption:	16V/70mA AC
Dimensions (W x H x D):	103 x 38 x 141 mm
Weight:	565g without power supply

The manufacturer reserves the right to alter the technical specifications without notice.



Available in silver or black finish