

## High Performance CD Auto Changer with MP3 and WMA (Windows Media® Audio) Decoders.

The DCM-500AE, a 5-disc carousel CD changers equipped with MP3 and WMA decoders, let you not only enjoy regular audio CDs, but also MP3 and WMA encoded CD-R/RW discs.



WMA MP3

### ■ CD-R/RW Playback

### ■ MP3 and WMA Decoders

The DCM-500AE play finalized CD-R/RW discs containing MP3 or WMA audio files. When they are in MP3 or WMA format, a single CD-R/RW disc can contain up to 10 times more tracks than an ordinary audio CD. CD-R/RW discs containing a large number of MP3/WMA files are ideal for use in long-play applications such as background music.

### ■ Advanced Multilevel Noise Shaping DAC

The DCM-500AE features a Multilevel Noise Shaping DAC. This multi-level modulation powerfully removes the adverse effects of jitter, and because it is built into the output amp, a clean analog output with suppressed high-frequency interference can be directly obtained.

### ■ 8-Times Oversampling Digital Filter

Increasing the oversampling frequency by a factor of eight makes possible an extraordinary degree of attenuation and reduces frequency irregularities in the audio range to an absolute minimum.

### ■ Remote Control IN/OUT

When the DCM-500AE is cable connected to an amplifier or receiver that supports the Remote Control IN/OUT feature, you can operate the DCM-500AE via the remote sensor on the amplifier or receiver. This feature is very handy when the DCM-500AE is placed in another room.

### ■ Full Selection of Program Playback

The DCM-500AE lets you combine up to 32 tracks from the five or fewer CDs which are loaded.

### ■ 3-Mode Random Playback

Full Random/Program Random/Disc Sequential Random

### ■ Intelligent Disc Scan

The Disc Skip button can rotate the carousel tray clockwise or counter-clockwise when searching for a disc. (Counter-clockwise rotation is operable only by remote controller.)

### ■ 20-Selection Music Calendar Display

### ■ Optical/Coaxial Digital Outputs

### ■ Headphone Jack

### Specifications

#### Audio Section

|                           |                 |
|---------------------------|-----------------|
| Frequency response        | 2 Hz - 20 kHz   |
| Dynamic range             | 98 dB           |
| Signal-to-noise ratio     | 108 dB          |
| Total harmonic distortion | 0.003%          |
| Channel separation        | 98 dB           |
| Line out level (Fix)      | 2.0 V rms       |
| Digital Output            | Optical/Coaxial |

#### General

|                   |                             |
|-------------------|-----------------------------|
| Power supply      | AC 230 V, 50 Hz             |
| Power consumption | 15 W                        |
| Dimensions        | 434(W) x 120(H) x 400(D) mm |
| Weight            | 6.3 kg                      |

\* Design and specifications are subject to change without notice.

\* "WMA" (Windows Media® Audio) is a new audio codec developed by Microsoft in the United States of America.



Black version is also available.