

## Pro-Ject Amp Box SE

Stereo power amp



### Good sound from sound technology

- Metal case shields the electronics from vibrational and electromagnetic interference
- Bi-Phase PWM-circuit (Pulse Width Modulation)
- Gold plated RCA/Phono sockets and loudspeaker terminals
- Outboard power supply included

### Features

- Small size allows easy placement
- Pro-Ject Audio digital amplifiers achieve 80% energy efficiency
- The Amp Box SE can be switched on & off remotely via a trigger signal. A 45cm long power-on cable is supplied for this purpose
- For bi- or tri amplification use, the remote power-on signal can be relayed to further units

### Technical specifications

Power output:	2 x 80W/125W at 8ohms/4ohms (both channels driven)
Frequency response:	10Hz - 50kHz (+0dB, -3)
Channel separation:	> 40dB at 20kHz
Noise floor:	> -90dB (A weighted)
THD:	< 0,1% at 90W
Gain:	26dB
Pre in:	1 pair RCA/Phono sockets
Input sensitivity:	1,5V
Input impedance:	100kohms
Speaker connectors:	4mm Ø banana plugs, spades connectors or naked wire
Trigger:	12V DC switching voltage
Trigger in and out:	2-pole co-axial Ø 2,5mm jack
Outboard power supply:	48V/2,5A DC, suitable for your country's mains supply
Power consumption:	48V/2,5A DC
Dimensions W x H x D (D with sockets):	103 x 72 x 144 (163)mm
Weight:	1.400g without power supply

The manufacturer reserves the right to alter the technical specifications without notice.



Available in silver or black finish